



## 128 MM EDF SCHEDA SPINTE E CONSUMI

CODICE	MOTORE			BATTERIE			CONSUMO		
	MARCA	MODELLO	KV	N CELLE	VOLT	LIPO	KG SPINTA	AMPERE	WATT
VF-128-01	TPPOWER	56/70	600	12	44,10	6000A/60C	8,400	129	5,239
VF-128-02	TPPOWER	56/70	600	14	50,30	6000A/60C	10,300	147	7,293
VF-128-03	TENSHOK	EZ5360B8Y	560	12	46,20	6000A/60C	6,700	80	3,696
VF-128-04	TENSHOK	EZ5360B8Y	560	14	54,04	6000A/60C	8,400	101	5,495
VF-128-05	TLF.SSS	56104	650	12	43,80	6000A/60C	8,900	130	5,913
VF-128-06	TLF.SSS	56104	650	14	49,80	6000A/60C	11,000	156	7,768
VF-128-07	TENSHOK	EZ5360B8Y	750	12	43,20	6000A/60C	10,400	156	6,739
VF-128-08	TENSHOK	EZ5360B6Y	750	14	49,40	6000A/60C	12,400	192	8,999
VF-128-09	TPPOWER	56/80	745	12	42,92	6000A/60C	11,800	198	8,498
VF-128-10	TPPOWER	56/80	745	14	49,20	6000A/60C	13,100	221	10,873

NOTA: Tutti i test sono stati effettuati con il labbro di aspirazione montato